



Fakra Socket Straight Male Pin Violet H Code Crimp
RG174 - 101-11-10187

Part Number:

101-11-10187



Basic Information

| | |
|-----------------|-------------|
| Color | Violet |
| Connector Type | Plug |
| Contact Type | Male Pin |
| Fastening Type | Push-On |
| Mounting Type | Cable Mount |
| Number of Ports | 1 |
| Orientation | Straight |

Mechanical Specification

| | |
|---------------------------|-------|
| Contact Termination Style | Crimp |
|---------------------------|-------|

Material Specification

| | |
|------------------|---------------|
| Contact Finish | Gold Plated |
| Contact Material | Copper Alloy |
| Shell Finish | Nickel Plated |
| Shell Material | Zinc Alloy |

Electrical Specification

| | |
|-----------------|-------|
| Cable Type | RG174 |
| Frequency - Max | 6GHz |
| Impedance | 50Ω |

How to Order

| | | | | | | | |
|-------------|------------------------------------------------------------------------------------|------------------------------------------------------------------------------------|------------------------------------------------------------------------------------|------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------|
| |  |  |  |  |  |  |  |
| Code | A | B | C | D | E | F | G |
| Color | Deep Black | Cream White | Signal Blue | Bordeaux Violet | Leaf Green | Brown | Blue Gray |
| Application | Radio with phantom supply | Radio without phantom supply | GPS telematics or navigation | GSM Cellular Phone | TV (UHF) | TV (VHF) | SDARS terrestrial |
| |  |  |  |  |  |  |  |
| Code | H | I | K | L | M | N | Z |
| Color | Violet | Beige | Curry Yellow | Carmine Red | Pastel Orange | Pastel Green | Water Blue |

Disclaimer

The information in this specification is subject to change without notice. Please confirm the latest version before use. Technical parameters are for reference only, and sufficient testing and verification should be conducted in actual applications.